

4 Channel Bridgeable Amplifier

General

| | |
|--------------------------------|---|
| Max.power output | 80 W x 4 (4 Ω) 130 W x 4 (2 Ω) 260 W x 2 (4 Ω Bridged) |
| RMS power output | 40W x 4 (4 Ω) 65 W x 4 (2 Ω) 130 W x 2 (4 Ω Bridged) |
| Frequency Response | 10 Hz to 70 kHz |
| Impedance | 2 Ω to 8 Ω |
| Total Harmonic Distortion(THD) | <0.05% |
| S/N Ratio | 94 dB |
| LPF | 80Hz |
| HPF | 40Hz-500Hz |
| RCA Terminals | 4ch |
| Speaker Terminals | Screw-type |
| Input Level control | 300mV - 6.5 V |